AirLink® XR90 5G High-Performance Multi-Network Vehicle Router

The supercharged AirLink XR90 is purpose-built for public safety and transit with available dual-5G cellular radios and dual independent 4×4 MU MIMO Wi-Fi 6 antennas. It is the highest performing, most flexible router in the Sierra portfolio. It supports complete device-to-cloud security, reduces your total cost of ownership with ALMS Out-of-Band management, and with the cartridge-based design, enables long-term expandability and upgradability.



AirLink® XR90 Single/Dual 5G

Expandable 5G

Single 5G: 5 Gigabit Ethernet Dual 5G: 6 Gigabit Ethernet

GNSS with Dead Reckoning

Dual 4×4 MU MIMO Wi-Fi 6

Single/Dual Serial

IP64 Rated

AirLinkOS with AirLink Premium



AirLink® XR90 - Router Specifications

KEY FEATURES

Cellular Radios	Single & Dual 5G LPWA for ALMS Out of Band Management	
Wi-Fi	Dual 4×4 MU MIMO Wi-Fi 6	
Ethernet	Single 5G: 4x Gigabit, 1x 5 Gigabit Ethernet Port Dual 5G: 5x Gigabit, 1x 5 Gigabit Ethernet Port	

KEY FEATURES Serial	Single/Dual RS-232 (DB9) with optional cables
GNSS	48 Channel GNSS with Dead Reckoning
CAN	CAN bus/OBD-II (J1979)/J1939)
1/0	5 GPIO
USB	USB 3.1 USB-C
Bluetooth	Selectable Bluetooth 4.x Classic or Bluetooth LE (Future)
IP Rating	Sealed Aluminum Housing (IP64 Rated)
Services	AirLink Premium
Operating System	AirLink OS
Management System	ALMS

Region	North America	ЕМЕА & АРАС
CELLULAR		
Variant	North America	EMEA, APAC
Technology	Single/Dual 5G	Single/Dual 5G
Peak Downlink (Theoretical)	4.14 Gbps	4.14 Gbps
Peak Uplink (Theoretical)	660 Mbps	660 Mbps
LTE Category	5G	5G
Region	NAM	EMEA, APAC
Radio	EM9190	EM9190
МІМО	Single/Dual 4×4	Single/Dual 4×4
RF Connectors	FAKRA	FAKRA
SIM	Dual SIM (Mini-2FF)	Dual SIM (Mini-2FF)
FREQUENCY BANDS		
5G Bands	n1, n2, n3, n5, n28, n41, n66, n71, n77, n78, n79 (NSA & SA Support) Future Variant adds support for: n7, n8, n12, n20, n25, n38, n40, n48 (NSA & SA Support)	n1, n2, n3, n5, n28, n41, n66, n71, n77, n78, n79 (NSA & SA Support) Future Variant adds support for: n7, n8, n12, n20, n25, n38, n40, n48 (NSA & SA Support)

3:44	5G Vehicle Router X	R90 Sierra Wireless
4G LTE Bands FREQUENCY BANDS	B1, B2, B3, B4, B5, B7, B8, B12, B13, B14, B17, B18, B19, B20, B25, B26, B28, B29, B30, B32, B34, B38, B39, B40, B41, B42, B46, B48, B66, B71	B1, B2, B3, B4, B5, B7, B8, B12, B13, B14, B17, B18, B19, B20, B25, B26, B28, B29, B30, B32, B34, B38, B39, B40, B41, B42, B46, B48, B66, B71
3G HSPA+ Bands	B1, B2, B3, B4, B5, B6, B8, B9, B19	B1, B2, B3, B4, B5, B6, B8, B9, B19
2G GPRS Bands	_	-
LPWA	B1, B2, B3, B4, B5, B8, B9, B10, B12, B13, B17, B18, B19, B20, B25, B26, B27, B28, B66	B1, B2, B3, B4, B5, B8, B9, B10, B12, B13, B17, B18, B19, B20, B25, B26, B27, B28, B66
WIRELESS CERTIFICATION		
Regulatory	FCC, IC/ISED, PTCRB	GCF, CE, RED, RCM, ESN
Carrier	AT&T, FirstNet® 4G, T-Mobile, Verizon, Rogers, Telus, Bell, CBRS	ВТ
Public Safety	FirstNet® 4G	ESN
Part Numbers	1104785 Single 5G 1104786 Dual 5G 1104757 XP 5G Cartridge (Optional)	1104722 Single 5G 1104723 Dual 5G 1104757 XP 5G Cartridge (Optional)

WI-FI (OPTIONAL)

Wi-Fi Standard	Wi-Fi 6 802.11ax
Access Point	Dual
Client (Depot/WAN)	Yes
Client & AP	Yes
Peak Throughput (Theoretical)	2400 Mbps
МІМО	Dual 4×4
Security	WPA2/3 Enterprise
Clients	128 per radio
SSID	4 per radio
Output Power	23.3 dBm per chain
Frequency	2.4/5 GHz
RF Connectors	FAKRA (Beige)

ENVIRONMENTAL

Operating Temperature	-30°C to +70°C / -22°F to +158°F
Storage Temperature	-40°C to +85°C / -40°F to +185°F
Humidity	95% RH @ 60°C
Military Specification	MIL-STD-810G (Shock, Vibration, Thermal Shock, Humidity)

ENVIRONMENTAL

IP Rating	IP64

INDUSTRY CERTIFICATIONS

Safety	IECEE Certification Bodies Scheme (CB Scheme), UL 60950
Vehicle Usage	E-Mark (72/245/EEC, 2009/19/EC), ISO7637- 2, SAE J1455 (Shock & Vibration, Electrical)
Environmental Directives	RoHS2, REACH, WEEE, Prop 65
Hazardous Environments	Class 1 Div 2 – Ambient temperatures of -30°C to +60°C IECEx & ATEX
Rail Usage	EN50155/EN45545 (Rolling Stock)

POWER

Input Voltage	7 to 36 VDC
Power Consumption	Dual 5G Peak: 68W (5.7A @12V) Standby 55mW: (4.5mA@12V)

Power ModesBuilt-in protection against voltage transients including 5 VDC engine cranking and +200 VDC load dump

Ignition Sense with time delay shutdown

SECURITY

AAA	802.1x /Radius authentication with Wi-Fi and Ethernet
Firewall	Stateful firewall with port forwarding, DMZ
WLAN Encryption	WPA2/WPA3 Personal/Enterprise FIPS 140-2

Firmware Update Secure Firmware Update

NETWORK AND ROUTING

Sierra Cognitive Wireless IPv4 and IPv6 Routing

Network Address Translation (NAT)

Port Forwarding DHCP Server IP Passthrough LAN Segmentation

IPv4 Passthrough and IPv6 Prefix Extension WAN/LAN Connection Policy Management

Policy-Based Routing Configurable MTU size Static Routing WAN Ethernet

NETWORK AND ROUTING

QoS	Application/Traffic Priority Queuing
WAN Monitors	Connection Failure Recovery
LAN (ETHERNET/USB)	
	USB to Ethernet
VPN	
	Integrated with ACM VPN Server IPsec protocol with IKEv1/IKEv2
	FIPS 140-2 Level 1 compliant
Encryption	AES128/AES192/AES256
Hashing	SHA256/SHA384/SHA512
Key Exchange	DHGroup14/15/16/17/18/19/20/21
	LAN to LAN and Host to LAN Up to 10 concurrent tunnels per link MOBIKE protocol IP compression Full/Split Tunnel Dead Peer Detection (DPD)

ROUTER MANAGEMENT INTERFACES

ALMS Local web user interface

REST API (Beta)

EDGE COMPUTING

	Support for Edge Compute Containerized Applications (Beta)
RAM ^{1,2}	200 MB
Storage (Flash) ¹	750 MB
СРИ	Quad Core ARMv8 64 bit
	¹ Approximation available to containers (not device total) ² Depends on other enabled features

AIRLINK SERVICES

Services AirLink Premium	

Support	24/7
Warranty	1 year standard warranty with up to 5 years extended warranty with current

_AIRLINK SERVICES	AirLink Premium subscription
Device Management	ALMS with Advanced Mobility Reporting
Software Updates	Unrestricted critical firmware updates
RELIABILITY	
МТВБ	Single 5G: 19.0 years Using Telcordia SR-332 Issue 3 Method 1
ACCESSORIES	
In The Box	XR90, DC Power cable, LPWA Antenna, Quick Start Guide, AirLink Premium Leaflet

Other Accessories (sold separately)


6001004 XR80/90/MP/LX I/O Cable 6001192 XR80/90/MP70 J1939 Y Cable 6001204 XR80/90/MP70 OBD-II Y Cable 6001350 XR80/90 Mounting Bracket 6001372 XR80/90 AC Adaptor, 24 VDC 6001406 XR80/90 DC Power Cable 6001409 XR80/90 RJ45 to Dual DB9 6001410 XR80/90 RJ45 to Single DB9 6001433 XR80/90 DIN Rail Mounting Bracket 6001440 XR80/90 FAKRA Replacement Kit (8 Pieces) 6001456 XR80/90 to MG90 Mounting Bracket 1104757 XR80/90 XP-5G XR-Cartridge Global & NAM For Antenna options visit: *here*

DIMENSIONS

Size	Base: 220mm x 170mm x 53mm
	Single XP: 220mm x 220mm x 53mm
	Dual XP: 268mm x 220mm x 53mm

Weight

Base: 2.06 Kg Single XP: 2.64 Kg Dual XP: 3.22 Kg



^{*}For carrier specific band support please refer to the hardware user guide.